

Car Antenna



ModelZDACA133173-

3/5ZDACA220290-3/5ZDACA330390-3/5

Frequency Range-MHz133;«173220;«290330;«390

Gain-dBi3/53/53/5

PolarizationVerticalVerticalVertical

VSWR;Ü1.5;Ü1.5;Ü1.5

Input impedance-¡,505050

Maximum Input power-W505050

ConnectorN/F-KN/F-KN/F-K

Size-mm;Ü85/120;Ü65/120;Ü55/110

Weight-g0.35-0.450.35-0.450.2-0.35

Operating temperature-jæ-40;«60-40;«60-40;«60



ModelZDACA450470-

5HZDACA8901880D-3/5ZDACA8802170D-3

Frequency Range-MHz450;«470890;«960/1710;«1880880;«960/1710;«2170

Gain-dBi5.53/53

PolarizationVerticalVerticalVertical

VSWR;Ü1.5;Ü2;Ü2

Input impedance-¡,505050

Maximum Input power-W505050

ConnectorN/F-KSMA-JSMA-J

Size-mm;Ü100230250

Weight-g0.359085

Operating temperature-jæ-40;«60-40;«60-40;«60